

ZyXEL Prestige 652R-13 3.40(FW.0) Release Note

Date: May 24, 2002

Supported Platforms:

ZyXEL Prestige firmware V3.40(FW.0) supports for P652R-13

Versions:

ZyNOS Version: V3.40(FW.0) | 5/24/2002

Bootbase Version: V1.03 | 3/5/2002 11:12:49

Notes:

1. The Prestige 652R-I, is an ADSL over ISDN security router with built-in powerful firewall capabilities and secure Virtual Private Network (VPN), which are designed for small and medium-sized businesses (SMBs), and enterprises' branch offices. The high -performance firewall capabilities and VPN secure data transmission over the public Internet and protect Internal network resources from unauthorized access.

Main features for FCS:

- Support Multi-Mode standard (ANSI T1.413, Issue 2; G.dmt(G.992.1); G.lite(G992.2)).
- 1 auto-sensing 10/100M Ethernet interface
- Support Multi-protocol over AAL5 (RFC2684)
- Support PPP over ATM AAL5 (RFC 2364)
- Support PPP over Ethernet (RFC2516)
- Support up to 8 PVCs
- DHCP Client, Sever and Relay
- RIP I/ RIP II supported.
- IP alias/IP Multicasting/Policy Routing
- TFTP/FTP server for firmware upgrade
- F4/F5 OAM
- Multi-NAT/SUA
- Dynamic DNS
- Firewall with Stateful Inspection, DoS (Denial of Services) supports
- Web-based Configurations
- Script configuration from WAN side (SPTGen)
- Transparent bridging VLAN-tagging support
- VPN (2 IPSec sessions)
- Dial back up

2. For PPPoE, system must turn off the PPP VJ header compression. The command is as following:
“ppp ipcp compress off”, this command is already added into “autoexec.net”
3. Alcatel modem code version is 2.7.35

Modification:

Modification in 3.40(FW.0)b10 (5/22/2002)

- Base on P652R-11 b19 firmware

Modification in 3.40(FW.0)b9 (5/22/2002)

- Base on P652R-11 b18 firmware

Modification in 3.40(FW.0)b8 (5/17/2002)

- Base on P652R-11 b17 firmware

Modification in 3.40(FW.0)b7 (5/15/2002)

- Base on P652R-11 b16 firmware

Modification in 3.40(FW.0)b6 (5/10/2002)

- Base on P652R-11 b14 firmware

Modification in 3.40(FW.0)b5 (4/9/2002)

- Base on P652R-11 b12 firmware

Modification in 3.40(FW.0)b4 (4/4/2002)

- Base on P652R-11 b11 firmware

Bug fixes:

Bug fixes in 3.40(Fw.0)b11 (5/23/2002)

- Fix the bug that Web atm loopback test can't work if set boot module debug flag=0x00.

Bug fixes in 3.40(Fw.0)b10 (5/22/2002)

- Fix the bug that config NAT in WEB (not save yet) will disconnect all connection.

Bug fixes in 3.40(Fw.0)b9 (5/22/2002)

- Fix the bug that while set customized service port > 8 will cause firewall rule dest. “ANY” address invisible.
- Fix the bug that WEB LAN subnetmask setting can't work.
- Fix the firewall ACL set services as none bug.
- Fix the bug that WEB timer server can't work well in NTP server mode.
- Fix the bug that set WEB time zone option will disable server ip field.

Bug fixes in 3.40(Fw.0)b8 (5/17/2002)

- Fix the bug that VPN phase 2 KB can't work.
- Fix the bug that enter SMT11 submenu cause dialout username = ?.

Bug fixes in 3.40(Fw.0)b7 (5/15/2002)

- Fix the bug that web can't upgrade firmware.
- Fix the bug that SMT24.10 ENTER key will delete the timer server value.
- Fix the bug that E-net default gateway is set, when wan is up cause system hang.
- Fix the bug that SMT delete ISP node, web wizard config at first time can't save VPI/VCI.
- Fix the bug that firewall log loss some information.

Bug fixes in 3.40(Fw.0)b6 (5/10/2002)

- Fix the bug that can't del firewall wan to lan dest. adds.
- Fix the bug that when PPP is connecting, change to RFC-1483 or E-net cause exception.
- Fix the bug that SMT delete default remote node, Web wizard config., then SMT11 shows set = 1,1,1,1

Known Bugs:

1. Manufactory Data in Bootbase

ZyNOS Version	: V3.40(FW.0) 5/24/2002 11:14:06
Bootbase Version	: V1.03 3/5/2002 11:12:49
Vendor Name	: ZyXEL Communications Corp.
Product Model	: Prestige 652R
ZyNOS ROM address	: bfc08000
System Type	: 6
MAC Address	: 00A0C5xxxxxx
Default Country Code	: FF
Boot Module Debug Flag	: 00
RomFile Version	: xx
RomFile Checksum	: ada6
ZyNOS Checksum	: c6d6
SNMP MIB level & OID	: 060102030405060708091011121314151617181920
Main Feature Bits	: 86
Other Feature Bits	:
	92 02 00 00 00 00 00 00 00-00 00 00 00 00 00 00 00
	00 00 00 00 00 00 00 00 00-00 00 13 00 00 00

2. Default ROM File Value Setting

- Menu 1: General Setup

<p style="text-align: center;">Menu 1 - General Setup</p> <p>Menu 1 - General Setup</p> <p>System Name= ? Location= Contact Person's Name=</p> <p>Route IP= Yes Bridge= No</p> <p>Press ENTER to Confirm or ESC to Cancel:</p>
--

- Menu 3.1: General Ethernet Setup

<p style="text-align: center;">Menu 3.1 - General Ethernet Setup</p> <p>Input Filter Sets: protocol filters= device filters= Output Filter Sets: protocol filters= device filters=</p> <p>Press ENTER to Confirm or ESC to Cancel:</p>
--

- Menu 3.2 TCP/IP and DHCP Ethernet Setup

<p style="text-align: center;">Menu 3.2 - TCP/IP and DHCP Ethernet Setup</p> <p>DHCP Setup DHCP= Server Client IP Pool Starting Address= 192.168.1.33 Size of Client IP Pool= 32 Primary DNS Server= 0.0.0.0 Secondary DNS Server= 0.0.0.0 Remote DHCP Server= N/A TCP/IP Setup: IP Address= 192.168.1.1 IP Subnet Mask= 255.255.255.0 RIP Direction= Both Version= RIP-2B Multicast= IGMP-v2 IP Policies= Edit IP Alias= No</p> <p>Press ENTER to Confirm or ESC to Cancel:</p>
--

• **Menu 4 Internet Access Setup**

```

Menu 4 - Internet Access Setup

ISP's Name= ChangeMe
Encapsulation= RFC 1483
Multiplexing= LLC-based
VPI #= 8
VCI #= 35
ATM QoS Type= UBR
    Peak Cell Rate (PCR)= 0
    Sustain Cell Rate (SCR)= 0
    Maximum Burst Size (MBS)= 0
My Login= N/A
My Password= N/A
ENET ENCAP Gateway= N/A
IP Address Assignment= Static
    IP Address= 0.0.0.0
Network Address Translation= SUA Only
    Address Mapping Set= N/A

Press ENTER to Confirm or ESC to Cancel:

```

• **Menu 11 Remote Node Setup**

```

Menu 11 - Remote Node Setup

1. ChangeMe (ISP, SUA)
2. _____
3. _____
4. _____
5. _____
6. _____
7. _____
8. _____

Enter Node # to Edit:

```

• **Menu 11.1 Remote Node Profile**

```

Menu 11.1 - Remote Node Profile

Rem Node Name= ChangeMe      Route= IP
Active= Yes                  Bridge= No

Encapsulation= RFC 1483      Edit IP/Bridge= No
Multiplexing= LLC-based      Edit ATM Options= No
Service Name= N/A            Telco Option:
Incoming:                    Allocated Budget(min)= N/A
    Rem Login= N/A            Period(hr)= N/A
    Rem Password= N/A         Schedule Sets= N/A
Outgoing:                    Nailed-Up Connection= N/A
    My Login= N/A
    My Password= N/A          Session Options:
    Authen= N/A               Edit Filter Sets= No
                               Idle Timeout(sec)= N/A

Press ENTER to Confirm or ESC to Cancel:

```

• **Menu 11.3 Remote Node Network Layer Options**

```
Menu 11.3 - Remote Node Network Layer Options

IP Options:                               Bridge Options:
IP Address Assignment= Static             Ethernet Addr Timeout(min)= N/A
Rem IP Addr= 0.0.0.0
Rem Subnet Mask= 0.0.0.0
My WAN Addr= 0.0.0.0

NAT= SUA Only
Address Mapping Set= N/A
Metric= 2
Private= No
RIP Direction= None
Version= RIP-1
Multicast= None
IP Policies=

Enter here to CONFIRM or ESC to CANCEL:
```

• **Menu 11.6 Remote Node ATM Layer Options**

```
Menu 11.6 - Remote Node ATM Layer Options
VPI/VCI (LLC-Multiplexing or PPP-Encapsulation)

VPI #= 8
VCI #= 35
ATM QoS Type= UBR
Peak Cell Rate (PCR)= 0
Sustain Cell Rate (SCR)= 0
Maximum Burst Size (MBS)= 0

Enter here to CONFIRM or ESC to CANCEL:
```

• **Menu 11.5 Remote Node Filter**

```
Menu 11.5 - Remote Node Filter

Input Filter Sets:
protocol filters=
device filters=
Output Filter Sets:
protocol filters=
device filters=

Enter here to CONFIRM or ESC to CANCEL:
```

• **Menu 12.1 IP Static Route Setup**

```
Menu 12.1 - IP Static Route Setup

1. _____
2. _____
3. _____
4. _____
5. _____
6. _____
7. _____
8. _____

Enter selection number:
```

- **Menu 12.1.1 Edit IP Static Route**

Menu 12.1.1 - Edit IP Static Route

Route #: 1
Route Name= ?
Active= No
Destination IP Address= ?
IP Subnet Mask= ?
Gateway IP Address= ?
Metric= 2
Private= No

Press ENTER to Confirm or ESC to Cancel:

- **Menu 12.3 Bridge Static Route Setup**

Menu 12.3 - Bridge Static Route Setup

1. _____
2. _____
3. _____
4. _____

Enter selection number:

- **Menu 12.3.1 - Edit Bridge Static Route**

Menu 12.3.1 - Edit Bridge Static Route

Route #: 1
Route Name= ?
Active= No
Ether Address= ?
IP Address=
Gateway Node= 1

Press ENTER to Confirm or ESC to Cancel:

- **Menu 15 - NAT Setup**

Menu 15 - NAT Setup

1. Address Mapping Sets
2. NAT Server Sets

Press ENTER to Confirm or ESC to Cancel:

- Menu 15.1 - Address Mapping Sets

```

Menu 15.1 - Address Mapping Sets

1.
2.
3.
4.
5.
6.
7.
8.
255. SUA (read only)

Press ENTER to Confirm or ESC to Cancel:

```

- Menu 15.1.1 – Address Mapping Rules

```

Menu 15.1.1 - Address Mapping Rules

Set Name= ?

Idx  Local Start IP  Local End IP  Global Start IP  Global End IP  Type
---  -
1.
2.
3.
4.
5.
6.
7.
8.
9.
10.

Action= None          Select Rule= N/A

Press ENTER to Confirm or ESC to Cancel:

```

- Menu 15.2 – NAT Server Sets

```

Menu 15.2 - NAT Server Sets

1. Server Set 1 (Used for SUA Only)
2. Server Set 2
3. Server Set 3
4. Server Set 4
5. Server Set 5
6. Server Set 6
7. Server Set 7
8. Server Set 8
9. Server Set 9
10. Server Set 10

Press ENTER to Confirm or ESC to Cancel:

```


Menu 15.2.1 –NAT Server Setup (Used for SUA Only)

```

Menu 15.2.1 - NAT Server Setup (Used for SUA Only)

Rule      Start Port No.    End Port No.    IP Address
-----
1.        Default          Default         0.0.0.0
2.         0                0              0.0.0.0
3.         0                0              0.0.0.0
4.         0                0              0.0.0.0
5.         0                0              0.0.0.0
6.         0                0              0.0.0.0
7.         0                0              0.0.0.0
8.         0                0              0.0.0.0
9.         0                0              0.0.0.0
10.        0                0              0.0.0.0
11.        0                0              0.0.0.0
12.        0                0              0.0.0.0

Press ENTER to Confirm or ESC to Cancel:

```

Menu 21.1 Filter Set Configuration

```

Menu 21.1 - Filter Set Configuration

Filter Set #    Comments          Filter Set #    Comments
-----
1              _____          7              _____
2      NetBIOS_WAN          8              _____
3      NetBIOS_LAN          9              _____
4      PPPoE                10             _____
5      TEL_FTP_WEB_SNM      11             _____
6      _____          12             _____

Enter Filter Set Number to Configure= 0

Edit Comments= N/A

Press ENTER to Confirm or ESC to Cancel:

```

Menu 21.1.2 Filter Rules Summary (for NetBIOS_WAN)

```

Menu 21.1.2 - Filter Rules Summary

# A Type          Filter Rules          M m n
-----
1 Y IP    Pr=6, SA=0.0.0.0, DA=0.0.0.0, DP=137          N D N
2 Y IP    Pr=6, SA=0.0.0.0, DA=0.0.0.0, DP=138          N D N
3 Y IP    Pr=6, SA=0.0.0.0, DA=0.0.0.0, DP=139          N D N
4 Y IP    Pr=17, SA=0.0.0.0, DA=0.0.0.0, DP=137          N D N
5 Y IP    Pr=17, SA=0.0.0.0, DA=0.0.0.0, DP=138          N D N
6 Y IP    Pr=17, SA=0.0.0.0, DA=0.0.0.0, DP=139          N D F

Enter Filter Rule Number (1-6) to Configure:

```

- **Menu 21.1.2.1 TCP/IP Filter Rule (for NetBIOS_WAN)**

Menu 21.1.2.1 - TCP/IP Filter Rule

Filter #: 2,1

Filter Type= TCP/IP Filter Rule

Active= Yes

IP Protocol= 6 IP Source Route= No

Destination: IP Addr= 0.0.0.0

IP Mask= 0.0.0.0

Port #= 137

Port # Comp= Equal

Source: IP Addr= 0.0.0.0

IP Mask= 0.0.0.0

Port #=

Port # Comp= None

TCP Estab= No

More= No Log= None

Action Matched= Drop

Action Not Matched= Check Next Rule

Press ENTER to Confirm or ESC to Cancel:

- **Menu 21.1.2.2 TCP/IP Filter Rule (for NetBIOS_WAN)**

Menu 21.1.2.2 - TCP/IP Filter Rule

Filter #: 1,2

Filter Type= TCP/IP Filter Rule

Active= Yes

IP Protocol= 6 IP Source Route= No

Destination: IP Addr= 0.0.0.0

IP Mask= 0.0.0.0

Port #= 138

Port # Comp= Equal

Source: IP Addr= 0.0.0.0

IP Mask= 0.0.0.0

Port #=

Port # Comp= None

TCP Estab= No

More= No Log= None

Action Matched= Drop

Action Not Matched= Check Next Rule

Press ENTER to Confirm or ESC to Cancel:

• Menu 21.1.2.3 TCP/IP Filter Rule (for NetBIOS_WAN)

```
Menu 21.1.2.3 - TCP/IP Filter Rule

Filter #: 2,3
Filter Type= TCP/IP Filter Rule
Active= Yes
IP Protocol= 6      IP Source Route= No
Destination: IP Addr= 0.0.0.0
              IP Mask= 0.0.0.0
              Port #= 139
              Port # Comp= Equal
Source: IP Addr= 0.0.0.0
        IP Mask= 0.0.0.0
        Port #=
        Port # Comp= None
TCP Estab= No
More= No      Log= None
Action Matched= Drop
Action Not Matched= Check Next Rule

Press ENTER to Confirm or ESC to Cancel:
```

• Menu 21.1.2.4 TCP/IP Filter Rule (for NetBIOS_WAN)

```
Menu 21.1.2.4 - TCP/IP Filter Rule

Filter #: 2,4
Filter Type= TCP/IP Filter Rule
Active= Yes
IP Protocol= 17     IP Source Route= No
Destination: IP Addr= 0.0.0.0
              IP Mask= 0.0.0.0
              Port #= 137
              Port # Comp= Equal
Source: IP Addr= 0.0.0.0
        IP Mask= 0.0.0.0
        Port #=
        Port # Comp= None
TCP Estab= N/A
More= No      Log= None
Action Matched= Drop
Action Not Matched= Check Next Rule

Press ENTER to Confirm or ESC to Cancel:
```

Menu 21.1.2.5 TCP/IP Filter Rule (for NetBIOS_WAN)

Menu 21.1.2.5 - TCP/IP Filter Rule

Filter #: 2,5

Filter Type= TCP/IP Filter Rule

Active= Yes

IP Protocol= 17 IP Source Route= No

Destination: IP Addr= 0.0.0.0

IP Mask= 0.0.0.0

Port #= 138

Port # Comp= Equal

Source: IP Addr= 0.0.0.0

IP Mask= 0.0.0.0

Port #=

Port # Comp= None

TCP Estab= N/A

More= No Log= None

Action Matched= Drop

Action Not Matched= Check Next Rule

Press ENTER to Confirm or ESC to Cancel:

Menu 21.1.2.6 TCP/IP Filter Rule (for NetBIOS_WAN)

Menu 21.1.2.6 - TCP/IP Filter Rule

Filter #: 2,6

Filter Type= TCP/IP Filter Rule

Active= Yes

IP Protocol= 17 IP Source Route= No

Destination: IP Addr= 0.0.0.0

IP Mask= 0.0.0.0

Port #= 139

Port # Comp= Equal

Source: IP Addr= 0.0.0.0

IP Mask= 0.0.0.0

Port #=

Port # Comp= None

TCP Estab= N/A

More= No Log= None

Action Matched= Drop

Action Not Matched= Forward

Press ENTER to Confirm or ESC to Cancel:

Menu 21.1.3 Filter Rules Summary (for NetBIOS_LAN)

Menu 21.1.3 - Filter Rules Summary

#	A	Type	Filter Rules	M	m	n
1	Y	IP	Pr=17, SA=0.0.0.0, SP=137, DA=0.0.0.0, DP=53	N	D	F
2	N					
3	N					
4	N					
5	N					
6	N					

Enter Filter Rule Number (1-6) to Configure:

- Menu 21.1.3.1 TCP/IP Filter Rule (for NetBIOS_LAN)

```

Menu 21.1.3.1 - TCP/IP Filter Rule

Filter #: 3,1
Filter Type= TCP/IP Filter Rule
Active= Yes
IP Protocol= 17      IP Source Route= No
Destination: IP Addr= 0.0.0.0
                IP Mask= 0.0.0.0
                Port #= 53
                Port # Comp= Equal
Source: IP Addr= 0.0.0.0
                IP Mask= 0.0.0.0
                Port #= 137
                Port # Comp= Equal
TCP Estab= N/A
More= No           Log= None
Action Matched= Drop
Action Not Matched= Forward

Press ENTER to Confirm or ESC to Cancel:

```

- Menu 21.1.4 Filter Rules Summary (for PPPoE)

```

Menu 21.1.4 - Filter Rules Summary

# A Type                      Filter Rules                      M m n
- - - - -
1 Y Gen  Off=12, Len=2, Mask=ffff, Value=8863      N F N
2 Y Gen  Off=12, Len=2, Mask=ffff, Value=8864      N F D
3 N
4 N
5 N
6 N

Enter Filter Rule Number (1-6) to Configure:

```

- Menu 21.1.4.1 Generic Filter Rule (for PPPoE)

```

Menu 21.1.4.1 - Generic Filter Rule

Filter #: 4,1
Filter Type= Generic Filter Rule
Active= Yes
Offset= 12
Length= 2
Mask= ffff
Value= 8863
More= No           Log= None
Action Matched= Forward
Action Not Matched= Check Next Rule

Press ENTER to Confirm or ESC to Cancel:

```

Menu 21.1.4.2 Generic Filter Rule (for PPPoE)

```

Menu 21.1.4.2 - Generic Filter Rule

Filter #: 4,2
Filter Type= Generic Filter Rule
Active= Yes
Offset= 12
Length= 2
Mask= ffff
Value= 8864
More= No           Log= None
Action Matched= Forward
Action Not Matched= Drop

Press ENTER to Confirm or ESC to Cancel:

```

Menu 21.1.5 Filter Rules Summary (for TEL_FTP_WEB_SNM)

```

Menu 21.1.5 - Filter Rules Summary

# A Type           Filter Rules           M m n
- - - - -
1 Y IP   Pr=6, SA=0.0.0.0, DA=0.0.0.0, DP=23   N D N
2 Y IP   Pr=6, SA=0.0.0.0, DA=0.0.0.0, DP=21   N D N
3 Y IP   Pr=6, SA=0.0.0.0, DA=0.0.0.0, DP=80   N D N
4 Y IP   Pr=17, SA=0.0.0.0, DA=0.0.0.0, DP=69   N D N
5 Y IP   Pr=17, SA=0.0.0.0, DA=0.0.0.0, DP=161  N D N
6 Y IP   Pr=17, SA=0.0.0.0, DA=0.0.0.0, DP=162  N D F

Enter Filter Rule Number (1-6) to Configure:

```

Menu 21.1.5.1 TCP/IP Filter Rule (for TEL_FTP_WEB_SNM)

```

Menu 21.1.5.1 - TCP/IP Filter Rule

Filter #: 5,1
Filter Type= TCP/IP Filter Rule
Active= Yes
IP Protocol= 6      IP Source Route= No
Destination: IP Addr= 0.0.0.0
                IP Mask= 0.0.0.0
                Port #= 23
                Port # Comp= Equal
Source: IP Addr= 0.0.0.0
                IP Mask= 0.0.0.0
                Port #=
                Port # Comp= None
TCP Estab= No
More= No           Log= None
Action Matched= Drop
Action Not Matched= Check Next Rule

Press ENTER to Confirm or ESC to Cancel:

```

• Menu 21.1.5.2 TCP/IP Filter Rule (for TEL_FTP_WEB_SNM)

```
Menu 21.1.5.2 - TCP/IP Filter Rule

Filter #: 5,2
Filter Type= TCP/IP Filter Rule
Active= Yes
IP Protocol= 6      IP Source Route= No
Destination: IP Addr= 0.0.0.0
               IP Mask= 0.0.0.0
               Port #= 21
               Port # Comp= Equal
Source: IP Addr= 0.0.0.0
        IP Mask= 0.0.0.0
        Port #=
        Port # Comp= None
TCP Estab= No
More= No      Log= None
Action Matched= Drop
Action Not Matched= Check Next Rule

Press ENTER to Confirm or ESC to Cancel:
```

• Menu 21.1.5.3 TCP/IP Filter Rule (for TEL_FTP_WEB_SNM)

```
Menu 21.1.5.3 - TCP/IP Filter Rule

Filter #: 5,3
Filter Type= TCP/IP Filter Rule
Active= Yes
IP Protocol= 6      IP Source Route= No
Destination: IP Addr= 0.0.0.0
               IP Mask= 0.0.0.0
               Port #= 80
               Port # Comp= Equal
Source: IP Addr= 0.0.0.0
        IP Mask= 0.0.0.0
        Port #=
        Port # Comp= None
TCP Estab= No
More= No      Log= None
Action Matched= Drop
Action Not Matched= Check Next Rule

Press ENTER to Confirm or ESC to Cancel:
```

• Menu 21.1.5.4 TCP/IP Filter Rule (for TEL_FTP_WEB_SNM)

```
Menu 21.1.5.4 - TCP/IP Filter Rule

Filter #: 5,4
Filter Type= TCP/IP Filter Rule
Active= Yes
IP Protocol= 17      IP Source Route= No
Destination: IP Addr= 0.0.0.0
                IP Mask= 0.0.0.0
                Port #= 69
                Port # Comp= Equal
Source: IP Addr= 0.0.0.0
                IP Mask= 0.0.0.0
                Port #=
                Port # Comp= None
TCP Estab= N/A
More= No          Log= None
Action Matched= Drop
Action Not Matched= Check Next Rule

Press ENTER to Confirm or ESC to Cancel:
```

• Menu 21.1.5.5 TCP/IP Filter Rule (for TEL_FTP_WEB_SNM)

```
Menu 21.1.5.5 - TCP/IP Filter Rule

Filter #: 5,5
Filter Type= TCP/IP Filter Rule
Active= Yes
IP Protocol= 17      IP Source Route= No
Destination: IP Addr= 0.0.0.0
                IP Mask= 0.0.0.0
                Port #= 161
                Port # Comp= Equal
Source: IP Addr= 0.0.0.0
                IP Mask= 0.0.0.0
                Port #=
                Port # Comp= None
TCP Estab= N/A
More= No          Log= None
Action Matched= Drop
Action Not Matched= Check Next Rule

Press ENTER to Confirm or ESC to Cancel:
```


• **Menu 21.1.5.6 TCP/IP Filter Rule (for TEL_FTP_WEB_SNM)**

```
Menu 21.1.5.6 - TCP/IP Filter Rule

Filter #: 5,6
Filter Type= TCP/IP Filter Rule
Active= Yes
IP Protocol= 17      IP Source Route= No
Destination: IP Addr= 0.0.0.0
                IP Mask= 0.0.0.0
                Port #= 162
                Port # Comp= Equal
Source: IP Addr= 0.0.0.0
                IP Mask= 0.0.0.0
                Port #=
                Port # Comp= None
TCP Estab= N/A
More= No           Log= None
Action Matched= Drop
Action Not Matched= Forward

Press ENTER to Confirm or ESC to Cancel:
```

• **Menu 21.2 Firewall Setup**

```
Menu 21.2 - Firewall Setup

The firewall protects against Denial of Service (DoS) attacks when
it is active. The default Policy sets

    1. allow all sessions originating from the LAN to the WAN and
    2. deny all sessions originating from the WAN to the LAN

You may define additional Policy rules or modify existing ones but
please exercise extreme caution in doing so

Active: No

LAN-to-WAN Set Name: ACL Default Set
WAN-to-LAN Set Name: ACL Default Set

Please configure the Firewall function through Web Configurator

Press ENTER to Confirm or ESC to Cancel:
```

• **Menu 22 - SNMP Configuration:**

```
Menu 22 - SNMP Configuration

SNMP:
Get Community= public
Set Community= public
Trusted Host= 0.0.0.0
Trap:
Community= public
Destination= 0.0.0.0

Press ENTER to Confirm or ESC to Cancel:
```

- **Menu 23 – System Password:**

```

Menu 23 - System Password

Old Password= ?
New Password= ?
Retype to confirm= ?

Enter here to CONFIRM or ESC to CANCEL:

```

- **Menu 24.2.2: System Maintenance – Change Console Port Speed**

```

Menu 24.2.2 - System Maintenance - Change Console Port Speed

Console Port Speed: 9600

Press ENTER to Confirm or ESC to Cancel:

```

- **Menu 24.3: System Maintenance – UNIX Syslog**

```

Menu 24.3.2 - System Maintenance - UNIX Syslog

UNIX Syslog:
Active= No
Syslog IP Address= ?
Log Facility= Local 1

Types:
CDR= No
Packet triggered= No
Filter log= No
PPP log= No

Press ENTER to Confirm or ESC to Cancel:

```

- **Menu 24.10: System Maintenance – Time and Date Setting**

```

Menu 24.10 - System Maintenance - Time and Date Setting

Use Time Server when Bootup= None
Time Server Address= N/A

Current Time:                06 : 14 : 33
New Time (hh:mm:ss):        06 : 14 : 33

Current Date:                2000 - 01 - 01
New Date (yyyy-mm-dd):      2000 - 01 - 01

Time Zone= GMT

Daylight Saving= No
Start Date (mm-dd):          01 - 00
End Date (mm-dd):            01 - 00

Press ENTER to Confirm or ESC to Cancel:

```

• **Menu 24.11: System Maintenance –Remote Management Control**

Menu 24.11 - Remote Management Control

TELNET Server:
Server Port = 23
Secured Client IP = 0.0.0.0

Server Access = LAN only

FTP Server:
Server Port = 21
Secured Client IP = 0.0.0.0

Server Access = LAN only

Web Server:
Server Port = 80
Secured Client IP = 0.0.0.0

Server Access = LAN only

Press ENTER to Confirm or ESC to Cancel:

• **Menu 25: IP Routing Policy Setup**

Menu 25 - IP Routing Policy Setup

Policy Set #	Name	Policy Set #	Name
1		7	
2		8	
3		9	
4		10	
5		11	
6		12	

Enter Policy Set Number to Configure= 0

Edit Name= N/A

Press ENTER to Confirm or ESC to Cancel:

• **Menu 26: Schedule Setup**

Menu 26 - Schedule Setup

Schedule Set #	Name	Schedule Set #	Name
1	AlwaysOn	7	
2		8	
3		9	
4		10	
5		11	
6		12	

Enter Schedule Set Number to Configure= 0

Edit Name= N/A

Press ENTER to Confirm or ESC to Cancel:

- Menu 26.1: Schedule Setup (for AlwaysOn)

```

Menu 26.1 Schedule Set Setup

Active= Yes
Start Date(yyyy-mm-dd)= 2000 - 01 - 01
How Often= Weekly
Once:
    Date(yyyy-mm-dd)= N/A
Weekdays:
    Sunday= Yes
    Monday= Yes
    Tuesday= Yes
    Wednesday= Yes
    Thursday= Yes
    Friday= Yes
    Saturday= Yes
Start Time(hh:mm)= 00 : 00
Duration(hh:mm)= 23 : 59
Action= Forced On

Press ENTER to Confirm or ESC to Cancel:

```

- Menu 27: VPN/IPSec Setup

```

Menu 27.1 - IPSec Summary

#      Name      A Local Addr Start - Local Addr End      Encap  IPSec Algorithm
Key Mgt Remote Addr Start - Remote Addr End      Secure Gw Addr
-----
001
002
003
004
005

Select Command=  None          Select Rule=  N/A

Press ENTER to Confirm or ESC to Cancel:

```

- Menu 27.1.1: IPSec Setup

```

Menu 27.1.1 - IPSec Setup

Index #= 1      Name= ?
Active= No

My IP Addr= 0.0.0.0
Secure Gateway Addr= 0.0.0.0
Protocol= 0
Local:  Addr Type= SINGLE
        IP Addr Start= 0.0.0.0      End= N/A
        Port Start= 0              End= N/A
Remote: Addr Type= N/A
        IP Addr Start= N/A          End= N/A
        Port Start= N/A            End= N/A
Enable Replay Detection= N/A
Key Management= N/A
Edit Key Management Setup= N/A

DELETE PROFILE:

```

- `ras> sys view autoexec.net`
 - `sys errctl 0`
 - `sys trcl level 5`
 - `sys trcl type 1180`
 - `sys trcp cr 64 96`
 - `sys trcl sw off`
 - `sys trcp sw off`
 - `ip tcp mss 512`
 - `ip tcp limit 2`
 - `ip tcp irtt 65000`
 - `ip tcp window 2`
 - `ip tcp ceiling 6000`
 - `ip rip activate`
 - `ip rip merge on`
 - `ip icmp discovery enif0 off`
 - `ppp ipcp compress off`
 - `sys wdog sw on`
 - `sys quick enable`